



YF-8160...100A AC Leakage Current Clamp Meter



CAT III 600V

Display

- 3-3/4 digit LCD with maximum reading of 4000.
- Overload indication.
- Low battery indication.

Features/Benefits

- Leakage current test function.
- Peak Hold.
- AC volts, AC current, Resistance, Continuity.
- Continuity test below 1000 ohms, buzzer will sound.
- Alternative for supply frequency.
- Low Pass Filter (LPF) function.
- 50/60Hz and wide frequency range 40Hz to 1000Hz.

Specifications

Maximum Current	100 Amps
Display Counts	4000
Maximum Conductor Size	35mm
AC Current Range	0.01mA to 100A, $\pm(1.5\%$ of rdg + 5 dgts)
AC Voltage Range	1V to 600V, $\pm(1.5\%$ of rdg + 5 dgts)
Resistance	0.1 ohm to 400 ohms $\pm(1.0\%$ + 5 dgts)
Leakage Current	Yes
Continuity Buzzer	Yes
Peak Hold	Yes
Dimensions	250mm)L) x 85mm (W) x 35MM (D)
Weight	342g